

SmartStick+

Documentation on HomeSeer's USB based Z-Wave stick. [Purchase SmartStick+](#)

Overview

SmartStick+ G3 is a USB Z-Wave interface that's designed to send and receive wireless Z-Wave commands to and from compatible smart home products in the home. SmartStick+ is compatible with most smart home systems including HomeSeer HS3 & HS4-powered software and hubs. Click the QR code to the right or visit homeseer.com/zwave-interfaces for more information on SmartStick+ G3.

SmartStick+ G3 Requirements

HS4 Version: 4.1.15.0 or later

Z-Wave version: 3.0.3.3 or later

[Backup/Restore to Smartstick G3](#)

Information on moving your Z-Wave network from an older interface to the new SmartStick G3.

[SmartStick+ G3 Driver Setup](#)

[SmartStick+ G2 Configuration](#)

[USB Configuration](#)

SmartStick+ G3 Specifications

Z-Wave Chip Type	700 Series
Z-Wave SDK	7.15 (or later)
Z-Wave Frequency	908 MHz (US)
Wireless Range	Up To 300 Ft LOS
Operating Temp Range	0°C to 40°C
Power & Data	USB
Certifications	Z-Wave Plus, FCC
Dimensions	1.75 x 0.75 x 0.4 (inches)